

# MODEL 40n

#### MODEL 40n Integrated Stereo Amplifier with Streaming Built-In

Digital heart and analog soul. MODEL 40n unlocks the high-resolution sound of your favorite digital music streams (Spotify, Apple Music, Pandora, Tidal, and more) and your own music file libraries over AirPlay, Bluetooth, and HEOS®. Enjoy audio from your TV and its connected devices using built-in HDMI ARC (Audio Return Channel) connectivity. Enjoy rich, warm, Marantz sound from any source.

- Just Add Speakers Everything else for The Most Musical Sound is built-in
- Built for Streaming Use with Spotify, Apple Music, Tidal, AirPlay, Bluetooth and more—powered by HEOS<sup>®</sup>
- Sound Master Tuned Expertly crafted and tuned for The Most
  Musical Sound
- Musical Power 70 watts per channel to drive your favorite speakers
- Voice Control Works with Amazon Alexa, Google Assistant, or Apple Siri
- Luxurious Industrial Design Adds class to any environment
- HDAM Circuit Unique technology preserves every detail in your favorite sounds
- Marantz Musical Phono EQ Built-in MM phono stage makes adding a turntable easy
- Whole-Home Hi-Fi Connect with HEOS Built-in speakers for a whole-home system that allows you to to sync or separate streams in each room



### Modern Musical Luxury









## MODEL 40n Technical Specifications

Output Power	
Rated Output Power	70W + 70W (8ohm) 100W + 100W (4ohm)
Features	
Power Amplifier Circuit	HDAM-SA3
Power Transformer	Double Shielded Toroidal
Volume	Electric
Bass / Treble / Mid / Balance Control	yes / yes / - / yes
Source Direct	yes
Frequency Response	5Hz - 100kHz
Total Harmonic Distortion	0.02% (20Hz - 20kHz, 8Ω)
Damping Factor	100
Input Sensitivity: Phono Input	2 mV / 47 kohm
Input Sensitivity: CD/LINE/RECORDER	220 mV / 20 kohm
Input Sensitivity: Power Amplifier Input	1.6 V / 15 kohm
SN Ratio	PHONO (MM): 87dB CD: 106dB
Terminal	
Phono Input	yes (MM) Marantz Musical Phono EQ
Ext. Pre Input (Power Amp Direct)	yes
Preout	no
Analog Input (include Phono) / REC Out (RCA)	4 (PHONO, CD, LINE, RECORDER) / 1 (RECORDER)
Optical Input	1
Coaxial Input	1
HDMI Input/Output	1 / 0 (ARC) PCM only
USB-A	1 (Rear), Mass Storage Class 5V/1A
Speaker Terminal	SPKT-1+
Remote Control Bus Terminal	yes (RC-5 In / Out)
Subwoofer Pre-out Low Pass Filter	Selectable 40 Hz / 60 Hz / 80 Hz / 100 Hz / 120 Hz



Control			
Арр			HEOS App
Remote Controller			System Remote (Amp and CD Player Control)
Other			
Product Dimensions	(W x H x D in inches)		17.4" x 5.1" x 17"
Weight in Ibs		36 lbs 13 Oz	
Packaging Dimensions (W x H x D in inches)			21" x 10" x 20.6"
Carton Weight (incl. product) in lbs			43 lbs 3 Oz
Power Consumption		220W, 0.3W (Standby)	
AC Inlet			yes
Quick Start Guide			Included
Cosmetic			
Panel Color			SG / BK
Front Center Panel			Aluminum
Side Cover			Aluminum
Top Cover			Steel
Edge-Lighting			yes (Dimmer)
Volume Knob		Aluminum	
Input Selector		Aluminum	
Bass/Treble/Balance/REC Out Sel knobs		Aluminum	
Power Button		Aluminum	
Chassis Material		SECC	
Bottom Layer			Thicker double layer
UPC			
USA MODE	L40N/U1B	747192135959	Black
USA MODE	140N/U1SG	747192135966	Silver Gold

Design and specifications are subject to change by Marantz without notice.

#### www.marantz.com

