marantz







NR1510

MARANTZ NR1510 SLIM 5.2CH 4K ULTRA HD AV RECEIVER WITH HEOS BUILT-IN

Experience exceptional audio performance from the slim profile Marantz NR1510 5.2ch 4K Ultra HD AV receiver that drives elevated surround sound and high-fidelity audio from a compact chassis. At half the height of a traditional AV receiver, the NR1510 features the latest in HDMI connectivity and delivers high-resolution surround sound from Dolby TrueHD and DTS-HD Master Audio. Stream music from popular online sources and control the NR1510 with voice control compatibility via Amazon Alexa, Google Assistant and Apple Siri.

Highlights

- · Slim profile that's half the height of a traditional AV receiver delivers exceptional performance and the most musical sound
- 5-channel discrete power amplifier, 50W per channel (8-ohm, 20Hz 20kHz, 0.08% THD)
- 6 HDMI inputs with full HDCP 2.3 support
- Supports Dolby Vision, Hybrid Log-Gamma (HLG), eARC and ALLM for enhanced picture and audio
- 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR10 and BT.2020
- Surround format support for Dolby TrueHD and DTS-HD Master Audio
- ALAC, FLAC and WAV lossless file decoding up to 24-bit/192-kHz for high-resolution listening
- HEOS Built-in for multi-room streaming, music streaming and voice control
- Built-in Wi-Fi with 2.4GHz/5GHz dual band support (dual antenna)
- Supports all major voice control agents and streaming services
- Integrated phono input to directly connect your turntable





































because music matters

maran

NR1510 MARANTZ NR1510 SLIM 5.2CH 4K ULTRA HD AV RECEIVER WITH HEOS BUILT-IN





FEATURES	NR1710	AUDIO
MULTICHANNEL SURROUND		Analog In / Ou
DTS HD Master / DTS:X / DTS Neural:X	0/-/-	Phono (MM) I
DTS Virtual:X	-	Digital In: Opt
IMAX Enhanced	-	Multi-Room C
Dolby TrueHD / Dolby Atmos/Dolby Atmos Height Virtualization	0/-/-	USB Audio / N
Dolby ProLogic IIz / Dolby Surround	-/-	Multichannel
Auro 3D / Auromatic	-/-	Subwoofer Ou
Multichannel Stereo	0	7.1 Multichan
Max Number of Processing (Preamp) Channels	5.1	OTHER
Audyssey	MultEQ	Speaker Term
Audyssey Dynamic EQ / Dynamic Volume	0 / 0	Speaker A / B
Compressed Audio Enhancer: MDAX2	0	Bi-Amp Drive
NETWORK		Multi-Room S
HEOS Multi-Room and Streaming / Network Audio Streaming	0/0	Front Inputs: A
Lossy Formats: MP3 / WMA / AAC	0/0/0	OTHERS
Lossless Formats: FLAC / ALAC / WAV	0/0/0	FL Display
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	0/0/0	Graphic User
DSD Audio Streaming	up to DSD5.6	ISF Certification
Gapless Playback	o (FLAC, WAV ,ALAC ,DSD)	GUI Language
AirPlay2 Audio Streaming	0	Setup Assista
Internet Radio (Tune In)	o (Tuneln)	Smart Select
Spotify connect / Deezer / TIDAL / Napster / Pandora / SiriusXM	0/0/0/0/0/0	Firmware Upd
Compatible with Remote APP (iOS/Android)	Marantz 2016 AVR Remote	Variable Cross
Ethernet / Wi-Fi	o / o (dual antenna/ dual band)	Optimized Bas
Bluetooth	0	Bass Sync
HDMI		ECO Mode
HDMI 4K 60Hz 4:4:4 resolution / HDCP 2.3	0/0	ECO Mode Auto Power O
	0/0	
4K 60Hz 4:4:4 resolution / HDCP 2.3	<u> </u>	Auto Power 0
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel)	0	Auto Power O Sleep Timer
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling	0	Auto Power O Sleep Timer SPECIFICAT
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling	-	Auto Power O Sleep Timer SPECIFICAT Number of Po
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI	-	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision	0 - - 0 0 (HDR10) / o / o	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through	0 - - 0 0 (HDR10) / o / o	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode	0 - - 0 0 (HDR10) / o / o	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI	0 - - 0 0 (HDR10) / o / o 0	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output GENERAL
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated	0 - - 0 0 (HDR10)/o/o 0	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output GENERAL System Remo
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated HEOS Link Compatibility: IR/ IP	0 - - 0 0 (HDR10)/o/o 0	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output GENERAL System Remo Power Consur
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated HEOS Link Compatibility: IR/ IP Multi-Room zones	0 0 0 (HDR10)/o/o 0 0 0	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output GENERAL System Remo Power Consur Power Consur
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated HEOS Link Compatibility: IR/ IP Multi-Room zones Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog	0 0 0 (HDR10)/o/o 0 0/-/-/-	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output GENERAL System Remo Power Consur Power Consur Standby Cons
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated HEOS Link Compatibility: IR/ IP Multi-Room zones Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog IP Control / RS232 Control / Web Control / App Control	0 0 0 (HDR10)/0/0 0 0 0/-/-/- 0/-/0/0	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output Power Output GENERAL System Remo Power Consur Standby Cons Maximum D
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated HEOS Link Compatibility: IR/ IP Multi-Room zones Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog IP Control / RS232 Control / Web Control / App Control Domotz Pro / IHIJI compatible	0 0 0 (HDR10)/0/0 0 0 0/-/-/- 0/-/0/0	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output Power Output GENERAL System Remo Power Consur Standby Cons Maximum D Antenna Horizi
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated HEOS Link Compatibility: IR/ IP Multi-Room zones Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog IP Control / RS232 Control / Web Control / App Control Domotz Pro / IHIJI compatible INPUTS/OUTPUTS	0 0 0 (HDR10)/0/0 0 0 0/-/-/- 0/-/0/0	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output GENERAL System Remo Power Consur Power Consur Power Consur Antenna Horiz Antenna Verti
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated HEOS Link Compatibility: IR/ IP Multi-Room zones Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog IP Control / RS232 Control / Web Control / App Control Domotz Pro / IHIJI compatible INPUTS/OUTPUTS VIDEO	0 0 0 (HDR10)/0/0 0 0 0/-/- 0/-/0/0 0/0	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output Power Output GENERAL System Remo Power Consur Standby Cons Maximum D Antenna Horiz Antenna Verti w/o Antenna:
4K 60Hz 4:4:4 resolution / HDCP 2.3 eARC (Enhanced Audio Return Channel) Analog to HDMI scaling HDMI to HDMI scaling GUI Overlay on HDMI HDR / HLG / Dolby Vision 3D Signal Pass-Through HDMI Pass-Through in Standby Mode MULTIROOM / CI HEOS Multi-Room Integrated HEOS Link Compatibility: IR/ IP Multi-Room zones Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog IP Control / RS232 Control / Web Control / App Control Domotz Pro / IHIJI compatible INPUTS/OUTPUTS VIDEO Composite In / Out	0 0 0(HDR10)/o/o 0 0 0/-/- 0/-/o/o 0/0 3/1	Auto Power O Sleep Timer SPECIFICAT Number of Po Number of Sp Power Output Power Output Power Output GENERAL System Remo Power Consur Power Consur Standby Cons Maximum D Antenna Horiz Antenna Verti w/o Antenna: Weight (lbs)

Analog In / Out		3 / -
Phono (MM) In		0
Digital In: Optical / Coaxial		1/1
Multi-Room Out: Analog / Digit	al	-/-
USB Audio / Made for iPod / M	ade for iPhone	0/-/-
Multichannel Pre Out		o (2.2) / -
Subwoofer Out		2
7.1 Multichannel Input		-
OTHER		
Speaker Terminal: Gold Plated S	Screw / Regular Screw	-/0
Speaker A / B		-
Bi-Amp Drive		-
Multi-Room Speaker Terminal		-
Front Inputs: Audio / Composite	e / Digital (Opt) / HDMI / USB	-/-/-/0/0
OTHERS		
FL Display		1 line
Graphic User Interface - GUI		Hybrid GUI
ISF Certification		-
GUI Languages		3
Setup Assistant		0
Smart Select		0
Firmware Update by Network /	USB	0/0
Variable Cross Over		0
Optimized Bass Redirection		0
Bass Sync		-
ECO Mode		0
Auto Power Off		0
Sleep Timer		0
SPECIFICATIONS		
Number of Poweramps		5
Number of Speaker Terminals		5
Power Output (8 ohm, 20 Hz - 2)	N kHz II N8% 2ch Drivel	50 W
Power Output (6 ohm, 1 kHz, 0.7		60 W
Power Output (6 ohm, 1 kHz, 10		100 W
GENERAL	70 ICH DHVE/	100 **
System Remote Control		RC040SR
Power Consumption in W		180
· · · · · · · · · · · · · · · · · · ·	/FCO on / off\ in \/\	-
Power Consumption No-Sound	(ECO OII / OII) III VV	
Standby Consumption in W		0.2 (with CEC 0.5)
Maximum Dimensions	(mm)	17.0 v 14.0 v 4.4
Antenna Horizontal: W x D x H		17.3 x 14.9 x 4.1
Antenna Vertical: W x D x H (mi	Ш	17.3 x 14.9 x 6.9
w/o Antenna: W x D x H (mm)		17.3 x 14.5 x 4.1
Weight (lbs)		18.1
UPC		
MD1E10H1D		

* This feature is not available in all countries.

Sound United Vista, CA 92081 United States The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks of or trademarks of DTS, lnc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

Black

699927241650

^{*} All specs can be subject to change.